

# DIMIC12

Selective programmable digital paging station for AC12.8



DIMIC12 is a selective programmable digital paging station with the possibility to communicate with different zones in your office. The DIMIC12 can be used for 12 different zones. When the DIMIC12 is used with AUDIOCONTROL12.8 you can allocate buttons to perform actions like opening a door, controlling a sound source, ring a bell or even start a series of commands.

This paging station is designed for use with AUDIOCONTROL12.8 and easy to configure via the host's graphical user interface.

DIMIC12 combines an inconspicuous and elegant design with a remarkable sound quality. It has speech-optimized sound processing and a unidirectional condenser microphone.

The unit has universal configuration of push buttons, 12 free configurable selection buttons, status LEDs, a push-to-talk button and multicolor paging status LED. Expandable with maximum 7 x DIMIC12S.

## TECHNICAL SPECIFICATIONS

<b>active</b>	Yes	<b>polar pattern</b>	uni-directional
<b>buttons</b>	12 programmable + Call + All Call	<b>indicator</b>	1 per button + multi-color status
<b>zones</b>	up to 12	<b>frequency range</b>	220 Hz - 20 kHz
<b>nominal output level</b>	775mV variable balanced	<b>lo-cut</b>	220 Hz, 6 dB/oct
<b>power type</b>	Phantom or external power supply	<b>external power supply</b>	12 - 24Vdc/75mA
<b>mic stem lenght in mm</b>	395	<b>connector</b>	RJ45
<b>cable lenght in m</b>	5	<b>cable type</b>	CAT5
<b>cut out dimensions in mm</b>	85 x 230	<b>width in mm</b>	110
<b>height in mm</b>	58	<b>depth in mm</b>	240
<b>weight in gr</b>	650	<b>supported main unit</b>	AUDIOCONTROL12.8
<b>Net weight product (kg)</b>	0,68		

[MORE PICTURES](#)



## ACCESSORIES



**RJ45SPLIT**

RJ45 Splitter : 1input, 4 output (MICPAT-4 or ZONE4R)



**DIMIC12S**

DIMIC12 extension for AUDIOCONTROL12.8